



**Yaskawa J7 Drive Program  
for the Carlsen 1hp 230 volt Inoxpa Mixer**

ALL SETTINGS ARE AT DEFAULT EXCEPT FOR THE FOLLOWING

ADDRESS	SET TO	ALTERNATE SETTING	DESCRIPTION
N-01	11 (SET THIS CODE FIRST)	N/A	3 WIRE CONTROL
N-15	50% OF DEFAULT	N/A	MINIMUM VOLTAGE
N-16	2.0	N/A	ACCEL TIME
N-17	1.0	N/A	DECEL TIME
N-32	MOTOR RATED AMPS	N/A	MOTOR FLA
N-37	0	N/A	S3 = 3 WIRE
N-38	5	N/A	S4 = RESET
N-47	1	N/A	PWR LOSS
N-59	4	N/A	COAST ON OT
N-60	100	N/A	OVER TORQUE

UPDATED: 5/16/08