



**Yaskawa P7 Drive Program
for the Waukesha 40 5 hp 460 volt Pump**

ALL SETTINGS ARE AT DEFAULT EXCEPT FOR THE FOLLOWING

ADDRESS	SET TO	ALTERNATE SETTING	DESCRIPTION
A1-03	3330 (SET THIS CODE FIRST)	N/A	3 WIRE CONTROL
B1-04	0	N/A	REVERSE ENABLE
C1-01	2	N/A	ACCEL TIME
C1-02	1	N/A	DECEL TIME
E2-01	4.0	N/A	MOTOR FLA
L3-01	0	N/A	STALLP ACCEL SEL
L3-04	0	N/A	STALLP DECEL SEL
L3-06	70	N/A	STALL PREV RUN
L4-05	0	N/A	SIGNAL LOSS
O1-03	1	N/A	DISPLAY UNITS

Updated 11/27/06

**Yaskawa P7 Drive Program
for the Waukesha 40 5 hp 230 volt Pump**

ALL SETTINGS ARE AT DEFAULT EXCEPT FOR THE FOLLOWING

ADDRESS	SET TO	ALTERNATE SETTING	DESCRIPTION
A1-03	3330 (SET THIS CODE FIRST)	N/A	3 WIRE CONTROL
B1-04	0	N/A	REVERSE ENABLE
C1-01	2	N/A	ACCEL TIME
C1-02	1	N/A	DECEL TIME
E2-01	9.0	N/A	MOTOR FLA
L3-01	0	N/A	STALLP ACCEL SEL
L3-04	0	N/A	STALLP DECEL SEL
L3-06	75	N/A	STALL PREV RUN
L4-05	0	N/A	SIGNAL LOSS
O1-03	1	N/A	DISPLAY UNITS

Note: On single phase pumps address L8-06 equals 25%

Updated 11/27/06

CARLSEN AND ASSOCIATES
1439 GROVE STREET • HEALDSBURG, CA 95404
PHONE (707) 431-2000 • FAX (707) 431-2005